

Buzzer for 3300 Series Digital Clock (V1)



- Wired internally to Sapling's 3300 Series Digital Clock
- Works in conjunction with Sapling's Elapsed Timer (3300 Series Digital Clock model)
- When a countdown reaches zero (00:00:00), the buzzer produces an audible sound to alert the completion of the countdown
- The clock can be programmed to sound the buzzer for a duration of 1 to 60 seconds

Specifications:

Dimensions:

Diameter: 12mm (1.2cm) +/- 0.2mm (0.02cm)
Height: 10mm (1cm) +/- 0.2mm (0.02cm)

Operating Temperature: 32°F to 122°F
0°C to 50°C

Storage Temperature: 5°F to -103°F
-15°C to -75°C

Decibel Level: 85 db/min*

Oscillation Frequency: 2300Hz +/- 400Hz

Operating Voltage: 4.0 - 7.0 VDC*

*(Buzzer is powered by the digital clock)

Rated Voltage: 5 VDC

Tone/Pulse Rate: Constant

Power: The Buzzer is powered by the digital clock

Color: Black

Ordering Information: A-BUZZ-3300-1

*Measured in an open air environment